

p.d Support

Common issues and resolutions for when using p.d.

Remote Desktop Issues

Using p.d over Remote Desktop can lead to a few issues if the host computer is not configured properly. Below are the most common issues and how to resolve them when using p.d in this scenario:

LoadLibrary failed

- **Error:** "LoadLibrary failed with error <#>: The parameter is incorrect"
 - **Explanation:** The work station video drivers are not loading properly due to a RDP (Remote Desktop Protocol) connection. p.d requires OpenGL, but many older graphics drivers do not support OpenGL over RDP.
 - **Solution:**
 1. Option 1: Have the user login at the actual work station and not use RDP.
 2. Option 2: Update the video drivers. Recent (~2020) video driver updates may have included support for RDP OpenGL acceleration. In the past only workstation level graphics cards (e.g.: NVIDIA Quadro) supported OpenGL over RDP, but now other graphics cards (e.g.: NVIDIA GeForce) have been updated to also support this.
-

Unstable p.d crashes AND/OR Missing CT Images and Structures

- **Error:** p.d may crash while performing specific tasks (e.g.: designing a bolus) and/or the CTs and structures are not displayed
 - **Explanation:** The work station may contain outdated libraries or drivers that conflict with the p.d library requirements.
 - **Solution:**
 1. Option 1: Put p.d into Windows 7 compatibility mode. Open p.d and from the main menu open the "About p.d..." dialog and select the option to "Set Windows 7 Compatibility Mode".
 2. Option 2: Right click the p.d executable, open the Properties option, select the Compatibility tab, and set the executable to run in Windows 7 compatibility mode.
-

Copyright © 2020-Present .decimal LLC. All Rights Reserved.
121 Central Park Place, Sanford, FL 32771
1-800-255-1613

From:

<http://apps.dotdecimal.com/> - **decimal App Documentation**

Permanent link:

<http://apps.dotdecimal.com/doku.php?id=support:pdotd:softwareissues&rev=1667223414>

Last update: **2022/10/31 13:36**

